

& J STROKE - REGULAR & SPECIAL
RATINGS AT 45°

CODE NO.	ASSEMBLY	DC OUTPUT (ma)	AC INPUT (volts)			MOUNTING DIMEN. (inches)	MOUNTING (<i>h</i>)
			1	2	3		
1Y1	Y1H1E	25	16	30	-	3/8	Eyelet
2Y1	Y1O1E	50	-	-	30	7/16	6-32 x 5/16 ^a
2Y2	Y1D1E	25	32	60	-	7/16	6-32 x 5/16 ^a
2Y3	Y1B1E	25	32	60	-	3/8	Eyelet
2Y4	Y1C1E neg. C.T.	50	-	-	30	3/8	Eyelet
2Y5	Y2H1E	25	32	60	-	3/8	Eyelet
2Y7	Y2H1S	25	32	60	-		-
2Y9	Y1C1E	50	-	-	30	3/8	-
3Y1	Y3H1E	25	48	90	-	3/8	Eyelet
4Y1	Y4H1E	25	65	-	-	3/8	Eyelet
4Y2	Y2C1S	50	-	-	60	1/2	6-32 x 1/4 ^b
4Y3	Y1B1S	50	-	-	30	5/8	6-32 x 1/4 ^a
4Y4	Y2D1S	25	65	120	-	1/2	6-32 x 3/8 ^a
4Y5	Y2D1E	25	65	120	-	3/8	Eyelet
4Y7	Y1H1E	25	-	-	30	1/2	Eyelet
4Y8	Y2C1E	50	-	-	60	3/8	Eyelet
5Y1	Y5H1E	25	80	150	-	3/8	-
6Y1	Y3D1E	25	97	180	-	1/2	Eyelet
6Y2	Y3C1E	50	-	-	90	1/2	Eyelet
6Y3	Y3D1S	25	97	180	-	11/16	6-32 x 5/16 ^a
6Y4	Y6H1E	25	97	180	-	1/2	Eyelet
8Y1	Y8H1E	30	130	240	-	1/2	Eyelet
8Y2	Y4C1S	50	-	-	120	13/16	6-32 x 5/16 ^a
8Y5	Y4D1E	25	130	240	-	1/2	Eyelet
8Y8	Y2B1E	50	-	-	60	11/16	Eyelet
8Y9	Y4C1E	50	-	-	120	1/2	Eyelet
8Y10	Y4D1S	25	130	240	-	13/16	6-32 x 5/16 ^a

Bulletin No. 274
(supersedes No. 225)
January 1959

CODE NO.	ASSEMBLY	DC OUTPUT (ma)	AC INPUT (volts)			MOUNTING DIMEN. (inches)	MOUNTING (4)
			1	2	3		
10Y1	Y5D1S	25	162	300	-	13/16	6-32 x 7/16 ^a
10Y2	Y5C1S	50	-	-	150	11/16	Eyelet
10Y5	Y5D1E	25	162	300	-	11/16	Eyelet
10Y6	Y10H1E	25	162	300	-	11/16	Eyelet
12Y1	Y6D1S	25	195	360	-	7/8	6-32 x 3/8 ^a
12Y2	Y12H1E	25	195	360	-	11/16	Eyelet
12Y3	Y6D1E	25	195	360	-	11/16	Eyelet
12Y4	Y3B1E	50	-	-	90	7/8	Eyelet
16Y1	Y8D1E	25	260	480	-	7/8	Eyelet
16Y2	Y4B1S	50	-	-	120	1-1/8	10-32 x 1/4 ^a
16Y3	Y8C1E	50	-	-	240	7/8	Eyelet
16Y4	Y4B1E	50	-	-	120	1-1/8	Eyelet
17Y1	Y17H1E	25	275	510	-	7/8	Eyelet
17Y2	Y17H1S	25	275	510	-	1-1/8	6-32 x 1/4 ^a
20Y1	Y10C1E	50	-	-	300	1-1/8	Eyelet
20Y2	Y10D1E	25	325	600	-	1-1/8	Eyelet
20Y4	Y5B1E	50	-	-	150	1-3/8	1 -
20Y7	Y20H1E	25	325	600	-	1-1/8	Eyelet
20Y10	Y5B1S	50	-	-	150	1-9/16	6-32 x 5/16 ^a
24Y1	Y12D1E	25	390	720	-	1-3/8	Eyelet
24Y2	Y6B1E	50	-	-	180	1-3/8	Eyelet
24Y3	Y12C1E	50	-	-	360	1-3/8	Eyelet
24Y4	Y6B1S	50	-	-	180	1-9/16	10-32 x 5/16 ^a
24Y5	Tripler-Three 8Y1	25	-	-	-	1-3/8	Eyelet
24Y9	Y24H1S	25	390	720	-	1-7/16	6-32 x 5/16 ^a
24Y10	Y12C1EG.T.Neg.	50	-	-	360	1-3/8	C.T. NEG.
24Y11	Y12D1E	25	390	720	-	1-3/8	8-32 x 3/8 ^a
25Y1	Y25H1E	25	405	750	-	1-3/8	Eyelet
28Y1	Y28H1E	25	455	840	-	1-3/8	Eyelet
28Y2	Y7B1S	50	-	-	210	1-11/16	10-32 x 3/8 ^b
28Y3	Y14D1E	25	455	840	-	1-3/8	Eyelet
28Y6	Y14D1S	25	455	840	-	-	-

Bulletin No. 274
(supersedes No. 225)
January 1959

CODE NO.	ASSEMBLY	DC OUTPUT (ma)	AC INPUT (volts)			MOUNTING DIMEN. (inches)	MOUNTING (L)
			1	2	3		
32Y1	Y16C1S	50	-	-	480	1-11/16	6-32 x 5/16 ^a
32Y2	Y16D1S	25	520	960	-	2-1/16	10-32 x 3/8 ^b
32Y3	Y8B1S	50	-	-	240	2-1/8	10-32 x 3/8 ^b
32Y6	Y8B1S	50	-	-	240	1-3/4	8-32 x 5/16 ^a
32Y7	Y32H1S	25	520	960	-	2-1/16	10-32 x 3/8 ^b
32Y9	Y32H1S	-	-	-	-	1-3/4	8-32 x 5/16 ^a
36Y1	Y36H1S	25	585	1080	-	1-3/4	8-32 x 5/16 ^a
1J1	J1H1E	65	16	30	-	3/8	-
2J1	J1C1S	130	-	-	30	7/16	6-32 x 5/16 ^a
2J2	J1D1S	65	32	60	-	7/16	6-32 x 5/16 ^a
2J3	J1D1E	65	32	60	-	3/8	Eyelet
2J4	J1C1E Neg.C.T.	130	-	-	30	3/8	Eyelet
2J5	J2H1E	65	32	60	-	3/8	Eyelet
2J7	J2H1S	65	32	60	-	-	-
2J9	J1C1E	130	-	-	30	3/8	-
3J1	J3H1E	65	48	90	-	3/8	Eyelet
4J1	J4H1E	65	65	-	-	3/8	Eyelet
4J2	J2C1S	130	-	-	60	1/2	6-32 x 1/4 ^a
4J3	J1B1S	130	-	-	30	5/8	6-32 x 1/4 ^a
4J4	J2D1S	65	65	120	-	1/2	6-32 x 3/8 ^a
4J5	J2D1E	65	65	120	-	3/8	Eyelet
4J7	J1B1E	130	-	-	30	1/2	Eyelet
4J8	J2C1E	130	-	-	60	3/8	Eyelet
5J1	J5H1E	65	80	150	-	3/8	-
6J1	J3D1E	65	97	180	-	1/2	Eyelet
6J2	J3C1E	130	-	-	90	1/2	Eyelet
6J3	J3D1S	65	97	180	-	11/16	6-32 x 5/16 ^a
6J4	J6H1E	65	97	180	-	1/2	Eyelet
8J1	J8H1E	65	130	240	-	1/2	Eyelet
8J2	J4C1S	130	-	-	120	13/16	6-32 x 5/16 ^a
8J5	J4D1E	65	130	240	-	1/2	Eyelet
8J8	J2B1E	130	-	-	60	11/16	Eyelet
8J9	J4C1E	130	-	-	120	1/2	Eyelet

Bulletin No. 274
(supersedes No. 225)
January 1959

Page 3

Refer to page 6 for explanation of notes 1, 2, 3, 4^a and 4^b.

CODE NO.	ASSEMBLY	DC OUTPUT (ma)	AC INPUT (volts)			MOUNTING DIMEN. (inches)	MOUNTING (4)
			1	2	3		
8J10	J4D1S	65	130	240	-	13/16	6-32 x 5/16a
10J1	J5D1S	65	162	300	-	13/16	6-32 x 7/16a
10J2	J5C1S	130	-	-	150	7/8	6-32 x 1/2a
10J4	J5C1E	130	-	-	150	11/16	Eyelet
10J5	J5D1E	65	162	300	-	11/16	Eyelet
10J6	J10H1E	65	162	300	-	11/16	Eyelet
12J1	J6D1S	65	195	360	-	7/8	6-32 x 3/8a
12J2	J12H1E	65	195	360	-	11/16	Eyelet
12J3	J6D1E	65	195	360	-	11/16	Eyelet
12J4	J3B1E	130	-	-	90	7/8	Eyelet
16J1	J8D1E	65	260	480	-	7/8	Eyelet
16J2	J4B1S	130	-	-	120	1-1/8	10-32 x 1/4a
16J3	J8C1E	130	-	-	240	7/8	Eyelet
16J4	J4B1E	130	-	-	120	1-1/8	Eyelet
17J1	J17H1E	65	275	510	-	7/8	Eyelet
20J1	J10C1E	130	-	-	300	1-1/8	Eyelet
20J2	J10D1E	65	325	600	-	1-1/8	Eyelet
20J4	J5B1E	130	-	-	150	1-3/8	-
20J7	J20H1E	65	325	600	-	1-1/8	-
20J10	J5B1S	130	-	-	150	1-9/16	6-32 x 5/16a
24J1	J12D1E	65	390	720	-	1-3/8	Eyelet
24J2	J6B1E	130	-	-	180	1-3/8	Eyelet
24J3	J12C1E	130	-	-	360	1-3/8	Eyelet
24J4	J6B1S	130	-	-	180	1-9/16	10-32 x 5/16a
24J9	J24H1S	65	390	720	-	1-7/16	6-32 x 5/16a
24J10	J12C1E	130	-	-	360	1-3/8	O.T. Neg.
25J1	J25H1E	65	405	750	-	1-3/8	Eyelet
28J1	J28H1E	65	455	840	-	1-3/8	Eyelet
28J2	J7H1S	130	-	-	210	1-11/16	10-32 x 3/8b
28J3	J14D1E	65	455	840	-	1-3/8	-
28J6	J14D1S	65	455	840	-	-	-

CODE NO.	ASSEMBLY	DC OUTPUT (ma)	AC INPUT (volts)			MOUNTING DIMEN.	MOUNTING (4)
			1	2	3		
32J1	J16C1S	130	-	-	480	1-11/16	6-32x 5/16a
32J2	J16D1S	65	520	960	-	2-1/16	10-32 x 3/8b
32J3	J8B1S	130	-	-	240	2-1/8	10-32 x 3/8b
32J6	J8B1S	130	-	-	240	1-3/4	8-32 x 5/16a
32J7	J32H1S	65	520	960	-	2-1/16	10-32 x 3/8b
36J1	J36H1S	65	585	1080	-	1-3/4	8-32 x 5/16a

Page 5

Bulletin No. 274
 (supersedes No. 225)
 January 1959

Refer to page 6 for explanation of notes 1, 2, 3, 4a and 4b.

1. Ratings for entire stack as HW rectifier w/cap. filter -
2. Rating for entire stack as HW rectifier with res-ind. load
3. Rating for bridge or center tap stacks
4. (a) Stud out one end
(b) Stud out both ends

(Y stacks require 47 ohm series resistor)
(J stacks require 33 ohm series resistor)

Note: All eyelet mounted assemblies have a clearance for #6 screw.

These ratings are not applicable to Hi-Temp stacks.